



## DC CONNECTOR KIT FOR FRONIUS SYMO 10.0 - 20.0 KW AND FRONIUS ECO



/ The DC connector kit enables the connection of both inputs in the event of MPP currents above 35 A and a cable cross section of more than 16 mm<sup>2</sup>, for example when using a DC Box. A cross section of 6 mm<sup>2</sup> - 25 mm<sup>2</sup> can be connected using the DC connector kit. The terminal is safe to touch. The DC connector kit is particularly suitable for use with the Fronius Symo 10.0 - 20.0 kW and Fronius Eco inverters.

### TECHNICAL DATA

TECHNICAL DATA	DC CONNECTOR KIT 10 – 27 kVA
Item number	4,251,015
Max. current	100 A
Cable cross section	6 mm <sup>2</sup> - 25 mm <sup>2</sup>
Cable type	Used for copper and aluminium cables - strand or wire, sector or circular <sup>1)</sup>
Torque	5.5 Nm / 50 lb-in
Clamping area of the screw joint	8 mm - 13 mm
Standards	IEC 60999:2000, UL508, UL486A, CSA C22.2

1) PV cables must be used.